

APPLICATION FOR UNITED STATES LETTERS PATENT

FOR

**METHOD AND SYSTEM FOR BIDIRECTIONAL  
BITWISE CONSTANT PROPOGATION BY  
ABSTRACT INTERPRETATION**

Inventors: Williams Ludwell Harrison, III  
Cotton Seed

Prepared by:  
Blakely, Sokoloff, Taylor & Zafman  
1279 Oakmead Parkway  
Sunnyvale, California 94086  
(408) 720-8300

"Express Mail" mailing label number EL617184389US

Date of Deposit October 11, 2001

I hereby certify that this paper or fee is being deposited with the United States Postal Service "Express Mail Post Office to Addressee" service under 37 CFR 1.10 on the date indicated above and is addressed to the Assistant Commissioner of Patents and Trademarks, Washington, D.C. 20231.

Geneva Walls

(Typed or printed name of person mailing paper or fee)

(Signature of person mailing paper or fee)

09975859-101101

# METHOD AND SYSTEM FOR BIDIRECTIONAL BITWISE CONSTANT PROPOGATION BY ABSTRACT INTERPRETATION

## FIELD OF THE INVENTION

[001] This invention relates to computer software programming language implementation systems, and more specifically to a computer software programming language implementation system that performs bidirectional bitwise constant propagation by abstract interpretation.

## BACKGROUND OF THE INVENTION

[002] There are several areas in which compiler optimization literature exists within the field of computer software programming language implementation systems. Well-known techniques for optimizing compilation use abstract interpretation based static analysis. The most important work in this field is the extensive work of Patrick and Radhia Cousot, and the derivative and related work of Samson Abramsky, Chris Hankin, Alan Mycroft, Flemming, and Nielson. This body of work is primarily foundational in nature, and does not emphasize the application of the techniques in a practical setting, e.g., an optimizing C compiler. Among applications of abstract interpretation, the most nearly related is the work on strictness analysis, which is a technique in which functions are analyzed to discover when they are strict in (dependent upon) their arguments in the sense that a non-terminating argument computation will mean non-



05/25/2010 10:10

**FIGURE 1** illustrates a computer system representing an integrated multi-processor, in which elements of the present invention may be implemented.

**Figure 3** illustrates a representation for the abstract domain 220 that facilitates efficient program analysis using the abstract semantics  $A_b$ , 241 and  $A$ , 242.

**Figure 5** illustrates a flow diagram of a method 500 for optimizing an implementation of a programming language.

## DETAILED DESCRIPTION

**[005]** A method and system for bidirectional bitwise constant propagation by abstract interpretation is disclosed. In one embodiment, the method performs optimizing an implementation of a programming language, comprising; analyzing one or more values computed by a program written in the programming language, wherein analyzing one or more values comprises; representing each bit within a value of the one or more values as an abstract element of a lattice having a set of abstract elements including  $0_A$ ,  $1_A$ ,  $\perp_A$  and  $T_A$ , wherein the lattice is an abstraction of a concrete domain containing 0, 1, and  $\perp$ ; analyzing one or more output bits that are produced by an operation in terms of one or more input bits that are input to the operation; and analyzing the input bits that are input to the operation in terms of the output bits that are produced by the operation.

**[006]** In the following description, for purposes of explanation, specific nomenclature is set forth to provide a thorough understanding of the present invention. However, it will be apparent to one skilled in the art that these specific details are not required in order to practice the present invention.

**[007]** Some portions of the detailed descriptions that follow are presented in terms of algorithms and symbolic representations of operations on data bits within a computer memory. These algorithmic descriptions and representations are the means used by those skilled in the data processing arts to most effectively convey the substance of their work to others skilled in the art. An algorithm is here, and generally, conceived to be a self-consistent sequence of

steps leading to a desired result. The steps are those requiring physical manipulations of physical quantities. Usually, though not necessarily, these quantities take the form of electrical or magnetic signals capable of being stored, transferred, combined, compared, and otherwise manipulated. It has proven convenient at times, principally for reasons of common usage, to refer to these signals as bits, values, elements, symbols, characters, terms, numbers, or the like.

[008] It should be borne in mind, however, that all of these and similar terms are to be associated with the appropriate physical quantities and are merely convenient labels applied to these quantities. Unless specifically stated otherwise as apparent from the following discussion, it is appreciated that throughout the description, discussions utilizing terms such as "processing" or "computing" or "calculating" or "determining" or "displaying" or the like, refer to the action and processes of a computer system, or similar electronic computing device, that manipulates and transforms data represented as physical (electronic) quantities within the computer system's registers and memories into other data similarly represented as physical quantities within the computer system memories or registers or other such information storage, transmission or display devices.

**[009]** The present invention also relates to apparatus for performing the operations herein. This apparatus may be specially constructed for the required purposes, or it may comprise a general-purpose computer selectively activated

or reconfigured by a computer program stored in the computer. Such a computer program may be stored in a computer readable storage medium, such as, but is not limited to, any type of disk including floppy disks, optical disks, CD-ROMs, and magnetic-optical disks, read-only memories (ROMs), random access memories (RAMs), EPROMs, EEPROMs, magnetic or optical cards, or any type of media suitable for storing electronic instructions, and each coupled to a computer system bus.

**[0010]** The algorithms and displays presented herein are not inherently related to any particular computer or other apparatus. Various general purpose systems may be used with programs in accordance with the teachings herein, or it may prove convenient to construct more specialized apparatus to perform the required method steps. The required structure for a variety of these systems will appear from the description below. In addition, the present invention is not described with reference to any particular programming language. It will be appreciated that a variety of programming languages may be used to implement the teachings of the invention as described herein.

**[0011]** Numerous compiler optimizations are driven by information concerning the values that are computed by a program, including which values are constant and, if so, what their values are. The discovery of such information is called constant propagation. The present method and system moves beyond traditional constant propagation in that: it

analyzes computations at the level of individual bits, so that a value may be discovered to be partially constant, i.e., constant in some bits but not in others; and

discovers that individual bits are undefined or unused by a program, with powerful consequences for optimization.

**[0012]** The present method may be performed efficiently on entire programs, provided that an alias analysis is available which partitions the memory accesses of the program into equivalence classes based on potential overlap. It requires essentially no type information from the program, and hence may be performed on high-level languages, assembly language, and machine code alike. The present method and system may be used to solve many problems, such as:

- constant folding (replacing computations by their constant values);
- dead code elimination (elimination of unused computations);
- elimination of undefined computations;
- algebraic simplification;
- determination of alignment of memory addresses; and
- semantics-preserving demotion of integer arithmetic to smaller precision (as a step towards vectorization using MMX-like instructions, for example).



**[0013]** The present method and system is presented as an instance of abstract interpretation, a technique whereby a formal correspondence between the actual semantics of a program and the semantics assigned to it under a program analysis is constructed. The reason for this rather theoretical exposition is that the present method and system is a family of methods rather than a single method; the family members have in common that they are all approximations of a limit that is given by the concrete semantics presented below

**[0014]** Figure 1 illustrates a computer system 100 representing an integrated multi-processor, in which elements of the present invention may be implemented. One embodiment of computer system 100 comprises a system bus 120 for communicating information, and a processor 110 coupled to bus 120 for processing information. Computer system 100 further comprises a random access memory (RAM) or other dynamic storage device 125 (referred to herein as main memory), coupled to bus 120 for storing information and instructions to be executed by processor 110. Main memory 125 also may be used for storing temporary variables or other intermediate information during execution of instructions by processor 110. Computer system 100 also may include a read only memory (ROM) and/or other static storage device 126 coupled to bus 120 for storing static information and instructions used by processor 110.

**[0015]** A data storage device 127 such as a magnetic disk or optical disc and its corresponding drive may also be coupled to computer system 100 for storing information and instructions. Computer system 100 can also be coupled to a

second I/O bus 150 via an I/O interface 130. A plurality of I/O devices may be coupled to I/O bus 150, including a display device 143, an input device (e.g., an alphanumeric input device 142 and/or a cursor control device 141). For example, video news clips and related information may be presented to the user on the display device 143.

**[0016]** The communication device 140 is for accessing other computers (servers or clients) via a network. The communication device 140 may comprise a modem, a network interface card, or other well known interface device, such as those used for coupling to Ethernet, token ring, or other types of networks.

**[0017]** Figure 2 illustrates an exemplary representation of the components of the present system and method, namely:

A concrete domain 210 which gives a meaning to values represented in binary form;

An abstract domain 220 which approximates the concrete domain 210 and which is appropriate for compile-time analysis of programs;

A concrete forward  $C_f$  231 and backward  $C_b$  252 semantics for basic operations on binary representations which describes their meaning in terms of the concrete domain 210; and

An abstract forward  $A_f$  242 and backward  $A_b$  241 semantics for the same operations which describes their meaning in terms of the abstract domain 220:

A method for computing the abstract backward semantics 241 of arbitrary boolean functions;

A representation of an abstract domain 220, illustrated in **Figure 3**, that facilitates efficient program analysis using the abstract semantics  $A_b$  241 and  $A_f$  242.

A method for computing an abstract forward  $M_f$  223 and backward meaning  $M_b$  224 from a program in a compiler intermediate language;

**[0018]** The present method allows a number of powerful program transformations and optimizations to be performed within an optimizing compiler, assembler, or post-link (executable) optimizer.

**[0019]** The present method and system makes several improvements over existing methods for constant propagation:

it provides constant information at the level of individual bits for a wide class of programs and operations. This effectively *enriches* the notion of constant value to include many computations that are considered non-constant by alternate approaches;

it provides both forward (production) and backward (consumption) information concerning constants. The backward information enables new classes of dead code elimination, algebraic simplification, demotion for vectorization, and other optimizations;

姓名	性别	年龄	籍贯	民族	文化程度	职业	住址	电话	备注
王德胜	男	45	山东	汉族	高中	教师	济南市	1234	
李小明	男	32	江苏	汉族	大学	工程师	南京市	5678	
张小红	女	28	广东	汉族	初中	护士	广州市	9012	
赵国强	男	55	河南	汉族	小学	工人	郑州市	3456	
刘小华	女	38	四川	汉族	高中	会计	成都市	7890	
陈大伟	男	42	浙江	汉族	大学	医生	杭州市	2345	
周丽娟	女	35	湖北	汉族	初中	售货员	武汉市	6789	
吴建刚	男	25	安徽	汉族	高中	学生	合肥市	0123	
孙文娟	女	48	湖南	汉族	小学	工人	长沙市	4567	
郑伟明	男	30	江西	汉族	大学	程序员	南昌市	8901	
冯小芳	女	22	广西	汉族	初中	售货员	南宁市	2109	
黄国强	男	50	福建	汉族	小学	工人	福州市	5432	
林小华	女	33	山西	汉族	高中	教师	太原市	9876	
周建刚	男	40	陕西	汉族	大学	工程师	西安市	1098	
吴丽娟	女	27	甘肃	汉族	初中	售货员	兰州市	3210	
郑伟明	男	37	宁夏	汉族	高中	工人	银川市	6543	
冯小华	女	24	青海	汉族	小学	工人	西宁市	9876	
黄国强	男	47	四川	汉族	初中	工人	成都市	2109	
林小华	女	34	重庆	汉族	高中	售货员	重庆市	5432	
周建刚	男	44	贵州	汉族	大学	教师	贵阳市	8765	
吴丽娟	女	29	云南	汉族	初中	售货员	昆明市	1098	
郑伟明	男	39	海南	汉族	高中	工人	海口市	3210	
冯小华	女	23	广东	汉族	小学	工人	广州市	6543	
黄国强	男	49	广西	汉族	初中	工人	南宁市	9876	
林小华	女	35	福建	汉族	高中	售货员	福州市	2109	
周建刚	男	45	江西	汉族	大学	教师	南昌市	5432	
吴丽娟	女	31	湖南	汉族	初中	售货员	长沙市	8765	
郑伟明	男	41	湖北	汉族	高中	工人	武汉市	1098	
冯小华	女	26	安徽	汉族	小学	工人	合肥市	3210	
黄国强	男	46	浙江	汉族	初中	工人	杭州市	6543	
林小华	女	36	江苏	汉族	高中	售货员	南京市	9876	
周建刚	男	46	山东	汉族	大学	教师	济南市	2109	
吴丽娟	女	31	河南	汉族	初中	售货员	郑州市	5432	
郑伟明	男	41	四川	汉族	高中	工人	成都市	8765	
冯小华	女	26	重庆	汉族	小学	工人	重庆市	1098	
黄国强	男	46	贵州	汉族	初中	工人	贵阳市	3210	
林小华	女	36	云南	汉族	高中	售货员	昆明市	6543	
周建刚	男	46	海南	汉族	大学	教师	海口市	9876	
吴丽娟	女	31	广东	汉族	初中	售货员	广州市	2109	
郑伟明	男	41	广西	汉族	高中	工人	南宁市	5432	
冯小华	女	26	福建	汉族	小学	工人	福州市	8765	
黄国强	男	46	江西	汉族	初中	工人	南昌市	1098	
林小华	女	36	湖南	汉族	高中	售货员	长沙市	3210	
周建刚	男	46	湖北	汉族	大学	教师	武汉市	6543	
吴丽娟	女	31	安徽	汉族	初中	售货员	合肥市	9876	
郑伟明	男	41	浙江	汉族	高中	工人	杭州市	2109	
冯小华	女	26	江苏	汉族	小学	工人	南京市	5432	
黄国强	男	46	山东	汉族	初中	工人	济南市	8765	
林小华	女	36	河南	汉族	高中	售货员	郑州市	1098	
周建刚	男	46							

**transitive:**  $x \subseteq y$  and  $y \subseteq z$  implies  $x \subseteq z$ .

antisymmetric:  $(x \sqsubseteq y)$  implies that either  $x=y$  or  $\text{not}(y \sqsubseteq x)$

x=y is true

$y \subseteq x$  is true but  $x \subseteq y$  is false

In the last case, we say the values are "incomparable".

09955910101

**[0020]Figure 4** illustrates an exemplary concrete domain according to one embodiment of the present invention. Consider a datum in binary form as computed by a running computer program. Each bit of the datum may have been assigned a definite value, either 0 or 1, by the program, or else its value may be undefined, ( $\perp$ ) having been assigned no definite value by the program. As an example of the latter, consider this example C program, and assume that unsigned integers have 32 bits:

**[0021]** In this example, all 32 bits of x are initially undefined, that is, they have been assigned no definite value by the program. The upper 16 bits of x are assigned definite values by the first assignment, but the lower 16 bits remain

[illegible]

```
int a, b, c, d, e;

a = 1;

b = 2;

c = a + b;

d = c << 16;

e = c & 0x0000FFFF;
```

**[0023]** In this example, `c` is assigned the 32-bit sum of `a` and `b`. The upper 16 bits of `c` are unused by the assignment to `d`, which shifts them away. They are likewise unused by the assignment to `e`, which masks them away. This example illustrates that many operations are insensitive to the values of some bits of their inputs, in that they would produce an equivalent output even if the values of those bits in their inputs were undefined.



(in terms of the concrete lattice) that is sufficient to produce the output required of the computation (according to the standard meaning of the computation). The backward and the forward value of a bit can never be incomparable (as would happen if, say, the forward value were 0 whereas the backward value were 1); for this condition would mean that the continuation of a computation required that the bit have a different value from that assigned to it by the prefix of the computation (according to the standard meanings of the prefix and the continuation). Such nonsensical meanings are ruled out as plainly unrealizable: the continuation of a computation must be given a meaning that is consistent with that given to the prefix in order for us to reason about (and realize) the computation. Consequently the backward value of a bit will always be comparable to ( $\sqsubseteq$ ) the forward value for the same bit.

### Concrete Semantics

#### Forward Semantics of Primitive Boolean Functions

[0028] The semantics of the bitwise operators (AND, OR, and NOT) are formulated on individual bits. Since these operators are bitwise, the meaning of AND, OR, and NOT on entire words will follow immediately: the meaning of each bit in the result will be the result of applying the single-bit meaning to the corresponding bits of the inputs.

AND	1	0	1
1	1	0	1
0	0	0	0



1	$\perp$	0	1
---	---------	---	---

Table 1

OR	$\perp$	0	1
$\perp$	$\perp$	$\perp$	1
0	$\perp$	0	1
1	1	1	1

Table 2

NOT	
$\perp$	$\perp$
0	1
1	0

Table 3

[0029] Tables 1, 2, and 3 above correspond exactly to the usual definitions of AND, OR, and NOT, in the case of 0 and 1 inputs. The AND and OR operators, however, produce non- $\perp$  results given  $\perp$  as an input, under some circumstances. They are said to be non-strict in that they do not require fully defined inputs in order to produce a fully defined output. This is a matter of definition; that is, they may be defined as producing a  $\perp$  result whenever presented with  $\perp$  on either input. The definition above, however, corresponds more precisely to the way they are used in assembly language programming and programming language implementation. For example, a program fragment like this

```
struct S { unsigned a:28; unsigned b:4 } x;
x.a = 0x1234567;
x.b = 0x8;
```

might be implemented in assembly language by something equivalent to the following:



**[0032]** The functions defined by the above tables are noted by AND(a,b), OR(a,b), and NOT(a). For example, AND(0,⊥) = 0, because the AND table gives 0 as the result of AND given inputs 0 and ⊥.

**[0033]** Consider Table 1 for AND above. The sub-table defined by columns and rows labeled 0 or 1 is identical to the familiar 2x2 boolean truth table for AND. The table has been extended to account for the possibility that one or both inputs may be  $\perp$ . The particular extension chosen is monotonic, which is a kind of continuity in a function that says that as an input is raised from an undefined ( $\perp$ ) value to a fully-defined value (0 or 1), the output of the function either rises or stays the same; in particular the output does not fall or move laterally from 0 to 1 or vice versa. The condition for the monotonicity of AND for example is that:

$$x \subseteq y \Rightarrow \text{AND}(x, z) \subseteq \text{AND}(y, z) \quad \forall x, y, z$$

**[0034]** It is easily verified that the tables written for AND, OR, and NOT are the maximal monotonic functions that are consistent with the basic 2-valued boolean functions AND, OR, and NOT, in that if any  $\perp$  in the output of the function were replaced by 0 or 1, the monotonicity of the function would be lost.

**[0035]** The semantics of complex boolean functions follows immediately from the AND, OR, and NOT tables above, provided that we can express the complex function in terms of AND, OR, and NOT operations. For example the XOR operator:

$$x \oplus y = \text{OR}(\text{AND}(x, \text{NOT}(y)), \text{AND}(y, \text{NOT}(x)))$$

is shown in Table 4, which is derived by simple application of the tables for AND, OR, and NOT to the XOR equation:

XOR	⊥	0	1
⊥	⊥	⊥	⊥
0	⊥	0	1
1	⊥	1	0

Table 4

### Backward Semantics of Primitive Boolean Functions

[0036] Consider the assignment

$$x = y \ \& \ z;$$

[0037] Suppose it is known that x is used in the continuation of this computation and that its value is 0. This demand on x translate into demands on y and z in that y and z must be sufficiently well-defined to cause x to be 0, but they need be no better defined. So y and z are defined so that they cause x to become 0, and nothing further (at least from the point of view of this single program fragment and what is known of the demands placed on x by the continuation). This idea may be captured in tables that are, in effect, the inverses of those given above for AND, OR, and NOT:

AND <sup>-1</sup> (input <sub>y</sub> input <sub>z</sub> output <sub>x</sub> )	input <sub>y</sub> input <sub>z</sub>
XX⊥	⊥⊥
OX0	0⊥
X00	⊥0
111	11

Table 5

OR <sup>1</sup> (input <sub>t1</sub> input <sub>t2</sub> output <sub>b</sub> )	input <sub>b1</sub> input <sub>b2</sub>
XX⊥	⊥⊥
1X1	1⊥
X11	⊥1
000	00

Table 6

NOT <sup>1</sup> (output <sub>b</sub> )	input <sub>b</sub>
⊥	⊥
0	1
1	0

Table 7

[0038] Consider Table 5 for AND<sup>1</sup>. It maps a pair of *forward* values for the inputs along with a *backward* value for the output, to a pair of *backward* values for the inputs. In other words, they map a demand on the output to a demand on the inputs, given the forward value of the inputs. The Xs in the table represent don't care values; i.e., any of ⊥, 0, or 1 can be substituted for the X. Since we require that the backward semantics be consistent with the forward semantics, the forward values are used for the inputs to the operator to obtain backward values for the input that are comparable to them.

[0039] Table 5 for AND<sup>1</sup> is ambiguous concerning the input 000; this case matches both 0X0 and X00. Either result (0⊥ or ⊥0) is correct; that is, the continuation will obtain the 0 it demands provided that either of the inputs to the AND are 0. Because of this ambiguity, there are in general multiple backward meanings for a program that are consistent with its forward meaning.

Interestingly, this is also a point where the function is non-monotonic. That is, either  $000 \rightarrow \perp 0$  or  $000 \rightarrow 0 \perp$  is chosen, and in either case the choice will cause the function to be non-monotonic. If we choose  $000 \rightarrow \perp 0$  is chosen, then since  $0 \perp 0 \rightarrow 0 \perp$ , the situation occurs that a rise in the second argument from  $\perp$  to 0 causes a fall in the first output bit from 0 to  $\perp$ ; and similarly if we choose  $000 \rightarrow 0 \perp$  is chosen.

**[0040]** Note that  $\text{NOT}^{-1}$  is defined independently of forward values: the requirements on its input are uniquely determined by its output, and they are necessarily consistent with the forward values for the inputs.

**[0041]** The syntax  $\text{AND}_1^{-1}(x, y, z)$  represents the first bit returned by  $\text{AND}^{-1}$  (i.e., the backward value of the first input), and  $\text{AND}_2^{-1}$  to represent the second bit returned by  $\text{AND}^{-1}$  (i.e., the backward value of the second input). These bits are indicated in Tables 5, 6, and 7 as  $\text{input}_{b_1}$  and  $\text{input}_{b_2}$  in the  $\text{AND}^{-1}$  table. A similar notation for  $\text{OR}_1^{-1}$  and  $\text{OR}_2^{-1}$  is used.

## Backward Semantics of Complex Boolean Functions

**[0042]** It may be desired to compute the backward semantics of an operator that is a complex expression over AND, OR, NOT, and one-bit variables. For example, consider the XOR operator:

$$x \oplus y = \text{OR}(\text{AND}(x, \text{NOT}(y)), \text{AND}(y, \text{NOT}(x)))$$

**[0043]** Here two one-bit variables,  $x$  and  $y$ , and an expression over  $x$  and  $y$  in terms of OR, AND, and NOT exist. Given a backward value for the  $\text{OR}(\text{AND}(x,$

NOT(y)), AND(y, NOT(x))) term as a whole, and forward values for the term and all of its subterms, the inverse operators  $OR^{-1}$ ,  $AND^{-1}$ , and  $NOT^{-1}$  may be applied top-down in order to derive backward values for x and y as well as all the other subterms. If it is assumed that the backward value for the term as a whole is 1, and that x and y have forward values of 0 and 1 respectively. Then the procedure for computing the backward value of each of the subterms is illustrated in the following Table 8:

$x \oplus y$	forward value argument 1	forward value argument 2	backward value	backward value argument 1	backward value argument 2
OR(AND(x,NOT(y)),AND(y,NOT(x)))	0	1	1	$\perp$	1
AND(x,NOT(y))	0	0	$\perp$	$\perp$	$\perp$
x			$\perp$		
NOT(y)	1		$\perp$	$\perp$	
y			$\perp$		
AND(y,NOT(x))	1	1	1	1	1
y			1		
NOT(x)	0		1	0	
x			0		

Table 8

[0044]The forward values are obtained from the forward semantics for AND, OR, and NOT, given forward values for x and y of 0 and 1 respectively. The initial backward value (1) for the term as a whole is given , and backward values for each of the subterms are derived. Working top-down: first apply  $OR^{-1}$  to the forward values of the subexpressions of the OR and the backward value of the term as a whole. The first subterm of the OR – AND(x,NOT(y)) – has a forward value of 0, and the second subterm of the OR – AND(y,NOT(x)) – a forward





term as a whole. This is referred to as procedure invert-expression in the text that follows.

[0046] This procedure may be used to create an inverse in tabular form for a complex operation, like XOR, one row at a time. In this case the results obtained from this procedure are shown in Table 9:

XOR <sup>1</sup> (input <sub>1</sub> input <sub>2</sub> output <sub>b</sub> )	input <sub>b1</sub> input <sub>b2</sub>
XX1	11
000	00
011	01
101	10
110	11

**Table 9**

The highlighted row is the one computed above.

### Forward Semantics of Operations on Words

[0047] The semantics presented heretofore are for operations on a single bit.

Consider the extension of these semantics to operations on words. A word may be denoted in one of two ways. The individual bit values may be written next to one another, as in 0110 (a 4-bit word). When richer expressions are needed for some of the bits, the bits of the word will be put between angle brackets <>, and separate them by commas, as in <AND(0,1), OR(1,0)> (a 2-bit word).

[0048] All operations on words can be seen as a collection of operations on individual bits, one such operation for each bit in the result word. Taking this view, each of the input words is merely a sequence of bits, and by naming each of the bits within the input words, the case of an operation on words is reduced to operations on individual bits that have already been considered.



**[0052]** The forward semantics of any binary operation on words can be expressed as a word of operations on individual bits. For example, addition on 2-bit integers can be expressed as

$$\text{ADD}(\langle a, b \rangle, \langle c, d \rangle) = \langle a \oplus c \oplus \text{AND}(b, d), b \oplus d \rangle$$

$$x \oplus y = \text{OR}(\text{AND}(x, \text{NOT}(y)), \text{AND}(y, \text{NOT}(x)))$$

## Backward Semantics of Operations on Words

## Bitwise Boolean Operators

$$\text{AND}^{-1}(\langle a_n, a_{n-1}, \dots, a_1 \rangle, \langle b_n, b_{n-1}, \dots, b_1 \rangle, \langle c_n, c_{n-1}, \dots, c_1 \rangle) =$$

$$(\langle \text{AND}_1^{-1}(a_n, b_n, c_n), \text{AND}_1^{-1}(a_{n-1}, b_{n-1}, c_{n-1}), \dots, \text{AND}_1^{-1}(a_1, b_1, c_1) \rangle,$$

$$\langle \text{AND}_2^{-1}(a_n, b_n, c_n), \text{AND}_2^{-1}(a_{n-1}, b_{n-1}, c_{n-1}), \dots, \text{AND}_2^{-1}(a_1, b_1, c_1) \rangle)$$

$$\begin{aligned} \text{OR}^{-1}(\langle a_n, a_{n-1}, \dots, a_1 \rangle, \langle b_n, b_{n-1}, \dots, b_1 \rangle, \langle c_n, c_{n-1}, \dots, c_1 \rangle) = \\ (\langle \text{OR}_1^{-1}(a_n, b_n, c_n), \text{OR}_1^{-1}(a_{n-1}, b_{n-1}, c_{n-1}), \dots, \text{OR}_1^{-1}(a_1, b_1, c_1) \rangle, \\ \langle \text{OR}_2^{-1}(a_n, b_n, c_n), \text{OR}_2^{-1}(a_{n-1}, b_{n-1}, c_{n-1}), \dots, \text{OR}_2^{-1}(a_1, b_1, c_1) \rangle) \\ \text{NOT}^{-1}(\langle a_n, a_{n-1}, \dots, a_1 \rangle) = \langle \text{NOT}^{-1}(a_n), \text{NOT}^{-1}(a_{n-1}), \dots, \text{NOT}^{-1}(a_1) \rangle \end{aligned}$$

**[0056]** As in the case of the single-bit versions, here the arguments to AND<sup>-1</sup> and OR<sup>-1</sup> are the forward values of the inputs and the backward value of the output. The result is two words, one representing the backward value of the first input, the other representing the backward value of the second input. In the case of NOT<sup>-1</sup>, the result is simply a word representing the backward value of the input.

### ***Shift Operators***

**[0057]** The backward semantics of shift operators simply transmit the demands on their outputs through to their inputs. For example, it may be written that:

$$\begin{aligned} \text{LEFT}^{-1}(\langle a_n, a_{n-1}, \dots, a_1 \rangle) &= \langle \perp, a_n, a_{n-1}, \dots, a_2 \rangle \\ \text{URIGHT}^{-1}(\langle a_n, a_{n-1}, \dots, a_1 \rangle) &= \langle a_{n-1}, a_{n-2}, \dots, a_1, \perp \rangle \\ \text{SRIGHT}^{-1}(\langle a_n, a_{n-1}, \dots, a_1 \rangle) &= \langle a_n \sqcup a_{n-1}, a_{n-2}, \dots, a_1, \perp \rangle \end{aligned}$$

**[0058]** Note that the semantics of SRIGHT<sup>-1</sup> reflect the fact that the sign bit is copied by the SRIGHT operator. This is an example of joining the backward values of all occurrences of a variable (the sign bit of the input, in this case) in order to produce the backward value of the variable in an expression in which it occurs more than once



090768-1

**[0062]** The abstraction, or systematic approximation, of the above concrete semantics may be considered in order to obtain a semantics that is appropriate for static program analysis.

**[0064]** Consider the abstract domain of **Figure 3**. The elements of the abstract domain are  $0_A$ ,  $1_A$ ,  $\perp_A$ ,  $T_A$ . Each abstract domain element represents a downward closed subset of the concrete domain. Such an abstract domain is known as a Hoare power domain. If a bit is described by an element of this abstract domain, then its value is one of the concrete domain elements contained in the abstract element. For example, if a bit is described by the abstract value  $1_A$ , it is known that its value in the concrete domain is either  $\perp$  or 1. It may be that the bit is undefined on one program execution path and defined to be 1 on a different program path, and that the abstract value  $1_A$  has been

used to summarize the set of possibilities for the bit over both execution paths.

In the backward sense, the abstract value of  $1_A$  means that the value is either unused in the continuation or else is used as the value 1. Note that this domain allows us to say when a value is definitely undefined or unused (this situation is represented by  $\perp_A$ ) but not to say when a value is definitely defined or definitely used: the abstract value  $0_A$ , for example, includes both the concrete  $\perp$  and 0 as possibilities.

### Abstract Semantics

#### Abstract Forward Semantics of Primitive Boolean Functions

AND	$\perp_A$	$0_A$	$1_A$	$T_A$
$\perp_A$	$\perp_A$	$0_A$	$\perp_A$	$0_A$
$0_A$	$0_A$	$0_A$	$0_A$	$0_A$
$1_A$	$\perp_A$	$0_A$	$1_A$	$T_A$
$T_A$	$0_A$	$0_A$	$T_A$	$T_A$

Table 10

OR	$\perp_A$	$0_A$	$1_A$	$T_A$
$\perp_A$	$\perp_A$	$\perp_A$	$1_A$	$1_A$
$0_A$	$\perp_A$	$0_A$	$1_A$	$T_A$
$1_A$	$1_A$	$1_A$	$1_A$	$1_A$
$T_A$	$1_A$	$T_A$	$1_A$	$T_A$

Table 11

NOT	
$\perp_A$	$\perp_A$
$0_A$	$1_A$
$1_A$	$0_A$
$T_A$	$T_A$

Table 12

**06957**

$$\text{AND}_{\text{abstract}}(x, y) = \sqcup \{ \text{Abs}(\text{AND}_{\text{concrete}}(a, b)) \mid a \in x, b \in y \}$$

**[0068]** In the case of  $\text{AND}(\perp_A, T_A)$ , the above equation resolves to

The *Abs* notation has been omitted since it is known by one of ordinary skill in the art.

**[0069]** The inverses of AND, OR, and NOT may be derived over the abstract domains from their concrete counterparts in exactly the same way as AND, OR,



and NOT over the abstract domain, namely by joining all the concrete cases represented by each abstract case. Tables 13, 14, and 15 result are as follows:

AND <sup>-1</sup> (input <sub>1</sub> input <sub>2</sub> output <sub>b</sub> )	input <sub>b1</sub> input <sub>b2</sub>
XX⊥ <sub>A</sub>	⊥ <sub>A</sub> ⊥ <sub>A</sub>
0 <sub>A</sub> ⊥ <sub>A</sub> 0 <sub>A</sub>	0 <sub>A</sub> ⊥ <sub>A</sub>
0 <sub>A</sub> 1 <sub>A</sub> 0 <sub>A</sub>	0 <sub>A</sub> ⊥ <sub>A</sub>
⊥ <sub>A</sub> 0 <sub>A</sub> 0 <sub>A</sub>	⊥ <sub>A</sub> 0 <sub>A</sub>
1 <sub>A</sub> 0 <sub>A</sub> 0 <sub>A</sub>	⊥ <sub>A</sub> 0 <sub>A</sub>
0 <sub>A</sub> 0 <sub>A</sub> 0 <sub>A</sub>	0 <sub>A</sub> 0 <sub>A</sub>
0 <sub>A</sub> T <sub>A</sub> 0 <sub>A</sub>	0 <sub>A</sub> 0 <sub>A</sub>
T <sub>A</sub> 0 <sub>A</sub> 0 <sub>A</sub>	0 <sub>A</sub> 0 <sub>A</sub>
1 <sub>A</sub> 1 <sub>A</sub> 1 <sub>A</sub>	1 <sub>A</sub> 1 <sub>A</sub>
1 <sub>A</sub> T <sub>A</sub> 1 <sub>A</sub>	1 <sub>A</sub> 1 <sub>A</sub>
T <sub>A</sub> 1 <sub>A</sub> 1 <sub>A</sub>	1 <sub>A</sub> 1 <sub>A</sub>
T <sub>A</sub> T <sub>A</sub> 1 <sub>A</sub>	1 <sub>A</sub> 1 <sub>A</sub>
1 <sub>A</sub> T <sub>A</sub> T <sub>A</sub>	1 <sub>A</sub> T <sub>A</sub>
T <sub>A</sub> 1 <sub>A</sub> T <sub>A</sub>	T <sub>A</sub> 1 <sub>A</sub>
T <sub>A</sub> T <sub>A</sub> T <sub>A</sub>	T <sub>A</sub> T <sub>A</sub>

Table 13

OR <sup>-1</sup> (input <sub>1</sub> input <sub>2</sub> output <sub>b</sub> )	input <sub>b1</sub> input <sub>b2</sub>
XX⊥ <sub>A</sub>	⊥ <sub>A</sub> ⊥ <sub>A</sub>
1 <sub>A</sub> ⊥ <sub>A</sub> 1 <sub>A</sub>	1 <sub>A</sub> ⊥ <sub>A</sub>
1 <sub>A</sub> 0 <sub>A</sub> 1 <sub>A</sub>	1 <sub>A</sub> ⊥ <sub>A</sub>
⊥ <sub>A</sub> 1 <sub>A</sub> 1 <sub>A</sub>	⊥ <sub>A</sub> 1 <sub>A</sub>
0 <sub>A</sub> 1 <sub>A</sub> 1 <sub>A</sub>	⊥ <sub>A</sub> 1 <sub>A</sub>
1 <sub>A</sub> 1 <sub>A</sub> 1 <sub>A</sub>	1 <sub>A</sub> 1 <sub>A</sub>
1 <sub>A</sub> T <sub>A</sub> 1 <sub>A</sub>	1 <sub>A</sub> 1 <sub>A</sub>
T <sub>A</sub> 1 <sub>A</sub> 1 <sub>A</sub>	1 <sub>A</sub> 1 <sub>A</sub>
0 <sub>A</sub> 0 <sub>A</sub> 0 <sub>A</sub>	0 <sub>A</sub> 0 <sub>A</sub>
0 <sub>A</sub> T <sub>A</sub> 0 <sub>A</sub>	0 <sub>A</sub> 0 <sub>A</sub>
T <sub>A</sub> 0 <sub>A</sub> 0 <sub>A</sub>	0 <sub>A</sub> 0 <sub>A</sub>
T <sub>A</sub> T <sub>A</sub> 0 <sub>A</sub>	0 <sub>A</sub> 0 <sub>A</sub>
0 <sub>A</sub> T <sub>A</sub> T <sub>A</sub>	0 <sub>A</sub> T <sub>A</sub>
T <sub>A</sub> 0 <sub>A</sub> T <sub>A</sub>	T <sub>A</sub> 0 <sub>A</sub>
T <sub>A</sub> T <sub>A</sub> T <sub>A</sub>	T <sub>A</sub> T <sub>A</sub>

Table 14

NOT <sup>-1</sup> (output <sub>b</sub> )	input <sub>b</sub>
⊥ <sub>A</sub>	⊥ <sub>A</sub>

**SECRET**

**[0070]** Given that backward values are consistent with (not higher than) the corresponding forward values, so these tables omit those cases in which output<sub>i</sub> is higher than the output<sub>i</sub> that would be produced by AND, OR, or NOT from the values of input<sub>i1</sub> and input<sub>i2</sub>.

**[0072]** To be able to assert a backward value of  $\perp$  provides important information that it is worth additional effort. The case of an AND operation in which one of

the operands is an immediate constant (an expression like `x & 0xFFFF0000` in a C program), shows that the immediate constant provides a concrete value of 0 or 1 and not an abstract value of  $0_A$  or  $1_A$ . Tables 16 and Table 17 result when these AND-with-immediate and OR-with-immediate operations are inverted:

$AND_k^{-1}$	0 (immediate)	1 (immediate)
$\perp_A$	$\perp_A$	$\perp_A$
$0_A$	$\perp_A$	$0_A$
$1_A$	$\perp_A$	$1_A$
$T_A$	$\perp_A$	$T_A$

Table 16

$OR_k^{-1}$	0 (immediate)	1 (immediate)
$\perp_A$	$\perp_A$	$\perp_A$
$0_A$	$0_A$	$\perp_A$
$1_A$	$1_A$	$\perp_A$
$T_A$	$T_A$	$\perp_A$

Table 17

[0073]The horizontal axis corresponds to the immediate (constant) input to the AND or OR, and the vertical axis corresponds to the result (output) from the AND or OR. The values within the table are the backward value of the varying input to the AND or OR. As can be seen,  $AND_k^{-1}$  in this case produces a backwards value of  $\perp$  whenever its immediate input is 0, and  $OR_k^{-1}$  produces a backwards value of  $\perp$  when its immediate input is 1. By considering the immediate 0 and 1 as concrete values, and working through the concrete values represented by each of the abstract output values, the table will be seen to follow directly from

the concrete inverses for  $\text{AND}^{-1}$  and  $\text{OR}^{-1}$ . Note that  $\text{AND}_k^{-1}$  and  $\text{OR}_k^{-1}$  are monotonic (for the reason that  $\perp$  is not a possibility for the immediate input).

**Abstract Forward Semantics of Complex Boolean Functions**

[0074] The observations we made concerning forward semantics of complex functions of 1-bit variables in the concrete domain hold, mutatis mutandis, in the abstract domain. Namely, the forward abstract semantics of such a function follows from the abstract semantics of AND, OR, and NOT applied to the expression of the function in terms of these primitive boolean operations. For example, the abstract semantics of the XOR operator

$$x \oplus y = \text{OR}(\text{AND}(x, \text{NOT}(y)), \text{AND}(y, \text{NOT}(x)))$$

results with Table 18, which can be derived by application of the tables for AND, OR, and NOT in the abstract domain to the XOR equation:

XOR	$\perp_A$	$0_A$	$1_A$	$T_A$
$\perp_A$	$\perp_A$	$\perp_A$	$\perp_A$	$\perp_A$
$0_A$	$\perp_A$	$0_A$	$1_A$	$T_A$
$1_A$	$\perp_A$	$1_A$	$0_A$	$T_A$
$T_A$	$\perp_A$	$T_A$	$T_A$	$T_A$

**Table 18**

[0075] There is however a second route possible in computing the abstract semantics of a complex function: one may first compute its concrete semantics, and inject the result into the abstract domain. In the case of XOR we would write

$$\text{XOR}_{\text{abstract}}(x,y) = \text{LI} \{ \text{XOR}_{\text{concrete}}(a,b) \mid a \in x, b \in y \}$$

0697536 : 101101

**[0076]** The abstract backward semantics of complex one bit operations can likewise be obtained by the procedure outlined for the computation of backward values for complex operations in the concrete domain (see the derivation of the table for XOR<sup>-1</sup> above). The operation is expressed under consideration in terms of AND, OR, and NOT, and then, given a backward value for the term as a whole and forward values for each of its inputs. The abstract operators AND<sup>-1</sup>, OR<sup>-1</sup>, and NOT<sup>-1</sup> are applied to the expression top-down in order to obtain backward values for each of the subterms. The backward value for each occurrence of a variable in the term is joined together in order to obtain the backward value for the variable in the term as a whole.

SKD

semantics, these routes result in the same abstract semantics; but in the backward case this is not so, because of the non-monotonicity of  $AND^{-1}$  and  $OR^{-1}$ . Consider this expression:

$OR(AND(a, AND(b, NOT(b))), b)$

[0078] If a concrete  $AND^{-1}$  is used that maps 000 to  $\perp 0$ , then the concrete backward semantics for this expression will assign a backward value of  $\perp$  to a (for all backward values for the expression as a whole and for all forward values for a and b). The abstraction of this concrete backward semantic will likewise assign a backward value of  $\perp_A$  to a. If the backward semantics are constructed for this expression by working in the abstract domain (beginning with an abstract value for the expression as a whole and abstract forward values for a and b, and applying  $AND^{-1}$ ,  $OR^{-1}$ , and  $NOT^{-1}$  in the abstract domain to derive abstract backward values for each subterm), a is given a backward abstract value of  $0_A$ . The reason, as indicated earlier, is that  $AND^{-1}$  in the abstract domain is weaker than its concrete counterpart, at exactly the point where the concrete  $AND^{-1}$  is non-monotonic. Note that either route gives a correct result, and the top-down compositional procedure is the basis for a practical method when backward values need be computed from a single-tuple of forward values and a backward value for the term as a whole. But to compute the inverse in the concrete domain and afterwards inject the result into the abstract domain will in general give a more accurate result. In this particular example, if the term  $AND(b, NOT(b))$  is simplified to an immediate 0, then we could apply  $AND_k^{-1}$  and not

0925647-101101

$$\text{SRIGHT}(\langle a_0, a_{n-1}, \dots, a_1 \rangle) = \langle a_0, a_0, a_{n-1}, \dots, a_2 \rangle$$

042390.P12543

$$\text{LEFT}^1(\langle a_n, a_{n-1}, \dots, a_1 \rangle) = \langle \perp_A, a_n, a_{n-1}, \dots, a_2 \rangle$$

$$\text{URIGHT}^1(\langle a_n, a_{n-1}, \dots, a_1 \rangle) = \langle a_{n-1}, a_{n-2}, \dots, a_1, \perp_A \rangle$$

$$\text{SRIGHT}^1(\langle a_n, a_{n-1}, \dots, a_1 \rangle) = \langle a_n \sqcup a_{n-1}, a_{n-2}, \dots, a_1, \perp_A \rangle$$

**[0081]** As mentioned, above the abstract backward semantics obtained by first computing the concrete backward semantics using procedure “invert-expression” and projecting the result into the abstract domain may be more accurate than the abstract backward semantics obtained by direct application of procedure invert-expression in the abstract domain; but the latter is sometimes a more practical technique, because it can be applied to a single-tuple of abstract values, for example, during program analysis, in cases where it might be impractical to compute the concrete backward semantics for an operation. This observation applies to operations on words as well as to operations on single bits.

### Analysis Method

**[0082]** The abstract forward and backward semantics, such as A<sub>1</sub>242 and A<sub>1</sub>241 may be rendered directly as a program analysis method for the purpose of bit-level constant propagation. The input to the method is a program represented in an intermediate language. The syntax for the intermediate language used to illustrate the method is given below. The result of the method is a map from aliases to abstract values. Abstract values are a simple representation of words



whose bits belong to the abstract domain, such as domain 300 of Figure 3 defined above. The term alias is defined below.

**Representing Abstract Values**

[0083]An element of the abstract domain 300 may be represented using two bits, there being four elements in the domain. By choosing the meaning of the bits carefully, however, the common operations on words may be made efficient. By designating the two bits as Z and O, and considering the following encoding of Table 19:

Z	O	abstract value
0	0	$\perp_A$
0	1	$0_A$
1	0	$1_A$
1	1	$T_A$

**Table 19**

[0084]In this representation, bit Z represents the “zero-ness” of a bit, and O represents the “one-ness” of the bit. A bit that has neither zero-ness nor one-ness is  $\perp_A$ ; a bit that has both is  $T_A$ .

[0085]Let AbstractValue be a structure with two integer members, called ZERO and ONE. For our purposes it is immaterial whether ZERO and ONE are signed or unsigned integers; because explicitly signed or unsigned operations will be used upon them where the distinction matters. An AbstractValue represents a

[illegible]

042390.P12543

[0088] This choice of representation for words in the abstract domain means that the basic operations on abstract values may be efficiently implemented. The procedures for  $\sqcup$  (JOIN),  $\bullet$  (MEET),  $\sqsubseteq$  (LE), AND, OR, NOT, LEFT, SRIGHT, and URIGHT on the AbstractValue type are as follows:

AbstractValue JOIN(AbstractValue V1, AbstractValue V2)

```
{  
  return AbstractValue(V1.ZERO | V2.ZERO, O1.ONE | O2.ONE)  
}
```

AbstractValue MEET(AbstractValue V1, AbstractValue V2)

```
{  
  return AbstractValue(V1.ZERO & V2.ZERO, O1.ONE & O2.ONE)  
}
```

bool LE(AbstractValue V1, AbstractValue V2)

```
{  
  return (V1.ZERO | V2.ZERO) == V2.ZERO && (V1.ONE | V2.ONE) ==  
  V2.ONE  
}
```

AbstractValue And(AbstractValue V1, AbstractValue V2)

```
{  
  return AbstractValue(V1.ZERO | V2.ZERO, O1.ONE & O2.ONE)  
}
```

AbstractValue Or(AbstractValue V1, AbstractValue V2)

```

{
    return AbstractValue(V1.ZERO & V2.ZERO, O1.ONE | O2.ONE)
}

AbstractValue Not(AbstractValue V1)
{
    return AbstractValue(V1.ONE, V1.ZERO)
}

AbstractValue Left(AbstractValue V1)
{
    return AbstractValue(~ (~ V1.ZERO << 1), V1.ONE << 1)
}

AbstractValue SRight(AbstractValue V1)
{
    return AbstractValue(~ (~ V1.ZERO >>> 1), V1.ONE >>> 1)
}

AbstractValue URight(AbstractValue V1)
{
    return AbstractValue(~ (~ V1.ZERO >> 1), V1.ONE >> 1)
}

```

**[0089]** The syntax >>> is written to indicate an arithmetic right shift (shift with sign-extension), and >> to indicate a logical right shift (shift with zero-extension).

**0697595**, **10101**

```
void And_inv(AbstractValue B, AbstractValue& V1, AbstractValue& V2)
```

```
void Or_inv(AbstractValue B, AbstractValue& V1, AbstractValue& V2)
```

042390.P12543

```
V2.ZERO &= B.ZERO

V2.ONE &= B.ONE

}

void Not_inv(AbstractValue B, AbstractValue& V1)
{
    V1.ZERO &= B.ONE
    V1.ONE &= B.ZERO
}

void Left_inv(AbstractValue B, AbstractValue& V1)
{
    V1.ZERO &= B.ZERO >> 1
    V1.ONE &= B.ONE >> 1
}

void SRight_inv(AbstractValue B, AbstractValue& V1)
{
    V1.ZERO &= (B.ZERO << 1) | SignBitOnly(B.ZERO)
    V1.ONE &= (B.ONE << 1) | SignBitOnly(B.ONE)
}

void URight_inv(AbstractValue B, AbstractValue& V1)
{
    V1.ZERO &= B.ZERO << 1
    V1.ONE &= B.ONE << 1
```

```

}

INT SignBitOnly(INT X)
{
    int N = sizeof(X) * CHAR_BIT
    return X >> (N-1) << (N-1)
}

```

### **An Example Intermediate Language**

[0091] The intermediate language contains two operations for operating on the state of the computer: a GET expression for reading from memory or registers, and a PUT expression for writing to memory or registers. It is assumed that all operations on the state are performed using these operations; that is, none of the other operations in the language have implicit side-effects on the state, at least not on the state that is subject to analysis by this method. Every PUT and GET in the program is assumed to have associated with it an alias, such that if two GETs or PUTs have different aliases, then there is no execution of the program under which those GETs and PUTs access the same storage location (memory address or register). Aliases are therefore an equivalence relation on the GETs and PUTs of the program such that all potentially dependent GETs and PUTs are assigned the same alias. In the case of a compiler temporary variable, virtual register, or other storage location that is accessed simply and transparently by the program, the GETs and PUTs that access that temporary

variable or virtual register will have the same alias, and no other PUTs and GETs in the program will have the same alias. Any alias analysis method that partitions the memory accesses of the program into equivalence classes according to potential dependence is adequate for the purpose of computing a correct set of aliases from the program; of course a sharper alias analysis method will yield a more precise result from the bitwise constant propagation method.

**[0092]** The representation of control flow in the intermediate language is irrelevant to the method, as the method is flow-insensitive.

**[0093]** For purposes of exposition, it is assumed that the statements of the intermediate language have the following syntax:

S : (PUT A E)  
E : (INTEGER [T] Z)  
| (BITAND E E)  
| (BITOR E E)  
| (BITNOT E)  
| (LEFT E E)  
| (SRIGHT E E)  
| (URIGHT E E)  
| (OP E E)  
| (GET [T] A)



A : alias

Z : integer

T : integer (number of bits)

[0094] The expressions of this language are typed by their size in bits. A type is written as [T], where T is the number of bits. For example, [10] denotes a 10-bit type. The atomic forms -- INTEGER and GET -- include a type specifier, whereas the remaining, compound forms have an implicit type which can be deduced from the types of their subexpressions.

[0095](PUT A E): This is the (abstract) form of a statement that writes to a storage location (memory or register). The expression E gives the value which is written to the location. A is an alias. The aliases must have the property that, given two GET or PUT expressions X1 and X2 whose aliases are different, there must be no execution of the program such that X1 and X2 access the same storage location.

[0096] In reality, an assignment to memory must include an expression for the address that is written, and an assignment to a register must include a specification of the register that is written; these are absent from our PUT expression, which has only an expression E for the value which is written to the memory location or register. This is because the information required by the

00952650

method concerning the storage location affected by the PUT is summarized in the alias A associated with the PUT. A PUT expression yields no value; it is as though its type were [0].

**[0097](INTEGER [T] Z):** This is the expression for an integer constant of T bits. Z is an integer that gives the value of the constant. For example, (integer [10] 17) is a 10-bit integer whose value is 17, or 0000010001 in binary.

**[0098](BITAND E E):** This expression returns the bitwise AND of its two arguments. The types of the two arguments must be equal and the type of the result is that of the arguments.

**[0099](BITOR E E):** This expression returns the bitwise OR of its arguments.

**[00100] (BITNOT E):** This expression returns the bitwise complement of its argument. The type of the result is the type of the argument.

**[00101] (LEFT E):** This expression returns the result of shifting its argument left by 1 bit. The vacated bit position is zero-filled.

**[00102] (SRIGHT E):** This expression returns the result of shifting its argument right by the 1 bit. The vacated bit position is filled with a copy of the most significant bit of the argument.

**[00103] (URIGHT E E):** This expression returns the result of shifting its argument right by the 1 bit. The vacated bit position is zero-filled.

**[00104] (GET [T] A):** This is the (abstract) form of an operation that reads from the state of the computer.





the abstract backward semantic is a set of inputs that may be different than the original inputs, but that will provide the same result.

[00109] Flow continues to processing block 545 where the inputs are analyzed to determine if they are partially constant values (as described above). At processing block 550, the compilation is optimized. For example, inputs that do not contribute to the result can be discarded. The process ends at block 599.

[00110] In an alternate embodiment, the method proceeds in two phases. In the first phase, a bipartite graph G is built over the aliases and PUT statements of the program. This graph expresses the flow of values between statements of the program. G is a kind of *dependence flow graph*. This graph can be either intraprocedural or interprocedural in scope, and the method operates intraprocedurally or interprocedurally accordingly.

[00111] In the second phase, the method maintains a set of nodes of G which are ready for processing. It then repeatedly removes and processes nodes from this set until the set is empty. If a processed node is a PUT statement, it evaluates the statement (by symbolically executing it), updates the abstract value associated with an alias of the PUT, and adds the alias to the working set if the updated value for the alias has changed. If the processed node is an alias, the method simply adds its successors in G to the set for evaluation.



If  $n$  corresponds to an alias, add the successors of  $n$  in  $G$  to  $Q$ .

If  $n$  corresponds to a statement of the form (PUT A E1), do:

let  $V = \text{Eval\_forward}(E1)$

if not( $\text{LE}(V, \text{ForwardValue}[A])$ ) then

$\text{ForwardValue}[A] = \text{JOIN}(\text{ForwardValue}[A], V)$

Add  $A$  to  $Q$

### Phase 3

For each alias  $M$ :

$\text{BackwardValue}[M] = \text{InitialBackwardValue}(M)$

Add the nodes corresponding to  $M$  to  $Q$ .

While  $Q$  is nonempty, do:

Let  $n$  be an element of  $Q$ . Remove  $n$  from  $Q$ .

If  $n$  corresponds to an alias, add the predecessors of  $n$  in  $G$  to  $Q$ .

If  $n$  corresponds to a statement of the form (PUT A E1), do:

let  $V = \text{BackwardValue}[A]$

$\text{Eval\_backward}(E1, V)$

end **Bitwise Constant Propagation Method**

[00113] The  $\text{ForwardValue}$  for each alias  $M$  is set to  $\text{InitialForwardValue}(M)$  at the outset of phase 2. The  $\text{InitialForwardValue}$  for an alias must reflect the initial state of memory for that alias and/or assignments to the alias that occur





```
    return SRight(Eval_forward(E1), Eval_forward(E2))
```

```
(URIGHT E1 E2):
```

```
    return URight(Eval_forward(E1), Eval_forward(E2))
```

```
(GET [T] A):
```

```
    return ForwardValue[A]
```

```
}
```

```
void Eval_backward (Expression E, AbstractValue F)
```

```
{
```

```
    AbstractValue V1, V2
```

```
    case E of
```

```
        (BITAND E1 E2):
```

```
            V1 = Eval_Forward(E1)
```

```
            V2 = Eval_Forward(E2)
```

```
            BitAnd_inv(F, V1, V2)
```

```
            Eval_Backward(E1, V1)
```

```
            Eval_Backward(E2, V2)
```

```
        (BITOR E1 E2):
```

```
            V1 = Eval_Forward(E1)
```

```
            V2 = Eval_Forward(E2)
```

```
            BitOr_inv(F, V1, V2)
```

```
            Eval_Backward(E1, V1)
```

```
            Eval_Backward(E2, V2)
```

(BITNOT E1):

V1 = Eval\_Forward(E1)

BitNot\_inv(F, V1)

Eval\_Backward(E1, V1)

(LEFT E1 E2):

V1 = Eval\_Forward(E1)

Left\_inv(F, V1)

Eval\_Backward(E1, V1)

(SRIGHT E1 E2):

V1 = Eval\_Forward(E1)

SRight\_inv(F, V1)

Eval\_Backward(E1, V1)

(URIGHT E1 E2):

V1 = Eval\_Forward(E1)

URight\_inv(F, V1)

Eval\_Backward(E1, V1)

(GET [T] A):

if not(LE(F, BackwardValue[A])) then

BackwardValue[A] = JOIN(BackwardValue[A], F)

Add A to Q

}

**[00114]** Note that the size of  $G$  (nodes + edges) is linear in the program text size. This follows from the fact that number of aliases in the program is less than the combined number of GETs and PUTs in the program, and hence the number of nodes in the graph is fewer than the number of GETs plus twice the number of PUTs in the program. The number of edges in  $G$  is no greater than the number of GETs plus the number of PUTs in the program.

### Example

**[00115]** Consider the following program in a C-like notation:

```
extern unsigned a, b, c, d, e, f;

static unsigned v, w, x, y, z;

v = a;

w = (v & 0xFFF0) | (b & 0x000F);

x = (w & 0xFF0F) | (c & 0x00F0);

y = (x & 0xF0FF) | (d & 0x0F00);

z = (y & 0x0FFF) | (e & 0xF000);

f = z;
```

Variables  $a$  through  $f$  are external, and are assigned initial forward and backward values of top ( $T_A T_A \dots T_A$ ) to represent their initial definitions and final uses.

Variables  $v$  through  $z$  are static (local), and we will assign them initial forward and backward values are assigned of bottom ( $\perp_A \perp_A \dots \perp_A$ ). This program is translated into statements in our intermediate language as follows:

(PUT v (GET [16] a))

(PUT w (BITOR (BITAND (GET [16] v) (INTEGER [16] 0xFFFF0))

(BITAND (GET [16] b) (INTEGER [16] 0x000F))))

(PUT x (BITOR (BITAND (GET [16] w) (INTEGER [16] 0xFF0F))

(BITAND (GET [16] c) (INTEGER [16] 0x00F0))))

(PUT y (BITOR (BITAND (GET [16] x) (INTEGER [16] 0xF0FF))

(BITAND (GET [16] d) (INTEGER [16] 0x0F00))))

(PUT z (BITOR (BITAND (GET [16] y) (INTEGER [16] 0x0FFF))

(BITAND (GET [16] e) (INTEGER [16] 0xF000))))

(PUT f (get [16] z))

**[00116]** The variable names themselves, are used as aliases, since there are no interesting alias relations in this program.

**[00117]** Bitwise Constant Propogation Method computes a ForwardValue of all top bits ( $T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A$ ) for all 11 of the aliases in the program. It computes the following BackwardValue array:

BackwardValue[a] =  $T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A$

BackwardValue[b] =  $T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A$

BackwardValue[c] =  $T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A$

BackwardValue[d] =  $T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A$

BackwardValue[e] =  $T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A$

BackwardValue[f] =  $T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A T_A$

**08-07-96**

[illegible]

**007-569**

[illegible][illegible][illegible][illegible]

**06-07-98**

**0007569**

[illegible]

[illegible]

where  $g$  is the chosen approximation of the operator in the forward direction. To see why, consider a simple pair of assignments (PUT  $y$  (INTEGER [16] 0x0000)) (PUT  $x$  (BITAND  $y$  0x0000)). Suppose an approximation is used of BITAND that produces a  $\perp$  bit in any position where either of its inputs is  $\perp$ ; but that the backward semantics for BITAND that is based on our discussion above is continued to be used, and therefore that delivers  $\perp$  backward values from some non- $\perp$  outputs. In a first analysis, it maybe concluded that  $y$  has a backward value of all  $\perp$  bits; that is, that  $y$  is unused. Its assignment may be deleted. If done however, a second analysis would conclude that  $x$  is undefined, whereas the original program clearly assigned  $x$  a value of 0x0000.

**[00120]** The method can be applied to an intermediate language in SSA form. In this case, a phi node is interpreted as a JOIN in the forward semantics, and as a simple transmitter of backward values in the backward analysis (the forward value for each input to the phi function is met (via  $\sqcap$ ) with the backward value for the phi to produce the backward value for the input).

**[00121]** It is straightforward to make this analysis conditional in the same sense that conditional constant propagation methods are conditional; namely, assignments that are guarded by conditionals are not activated until it is determined that the predicates that guard them are true. Method BCP can be trivially modified, by adding a notion of activated nodes in  $G$ , to provide this additional power.

**[00122]** A method and system for bidirectional bitwise constant propagation by abstract interpretation is disclosed. Although the present invention has been described with respect to specific examples and subsystems, it will be apparent to those of ordinary skill in the art that the invention is not limited to these specific examples or subsystems but extends to other embodiments as well. The present invention includes all of these other embodiments as specified in the claims that follow.

FOI T O T 65852660